

Thin Client

**P9002**



## Praim P9002, PCoIP<sup>®</sup> zero client with Teradici TERA2321 processor

- Zero client technology with Teradici TERA2321 processor
- Dual DVI with resolution up to 1920x1200
- Low power consumption , less than 4 W
- Top performances
- Fanless, silent, efficient and secure
- 4 USB external ports
- Very small size, it can be directly installed on the back of an LCD monitor

CERTIFIED FOR



Transforming Enterprise Computing

ITALY (HQ)

PRAIM SRL - VIA EZIO MACCANI, 191  
38121 TRENTO (TN)  
ITALY

p: +39 0461 420517 | f: +39 0461 420581

INFO@PRAIM.COM - WWW.PRAIM.COM

UNITED KINGDOM

PRAIM LTD - LAKESIDE HOUSE, 1 FURZEGROUND WAY  
STOCKLEY PARK, UXBRIDGE, UB11 1BD  
UNITED KINGDOM

p: +44 (0)20-8622 3031 | f: +44 (0)20-8622 3303

INFO@PRAIM.COM - WWW.PRAIM.CO.UK

| Technical specifications                                | P9002   |
|---|---|
| Processor/ Chipset                                      | Teradici TERA2321 PCoIP® Processor  |
| Power supply  | esterno 100/240VAC 50/60Hz, 24W, DC 12V/2A                                    |
| Power consumption: active / stand-by                    | 8W / 0,4W   |
| Device dim. with stand, weight / Packaging dim., weight | 42 (L) x 198 (H) x 140 (P) mm, 0,95Kg / 85 (L) x 303 (H) x 295 (P) mm, 2,0 Kg |
| Device marks / Power Supply marks                       | CE, FCC / CE, FCC Class B, GS TUV,UL  |
| Temperature range / humidity                            | 0° ÷ 40° / 20% ÷ 80%  |
| Security lock   | Kensington  |
| Display resolution / Colors                             | Up to 1920x1200 pixels  |
| RAM Memory / Flash memory                               | 32-bit DDR3-1066 512MB SDRAM  |
| <b>Peripherals</b>                                      |   |
| USB ports   | 4 x USB 2.0 ports (2 front + 2 rear)  |
| LAN Ethernet  | 10/100/1000 BaseT Ethernet RJ45   |
| Monitor   | 1 DVI-I port + 1 DVI-D port   |
| Audio In MIC / Audio Out Headphones                     | 1 x 1/8 inch jack / 2 x 1/8 inch jack (1 front + 1 rear)                      |
| <b>Protocols and resident clients</b>                   |   |
| Teradici Client   | Native PCoIP Teradici   |
| <b>Options</b>  |   |
|   | Part Number   |
| USB to Parallel cable adapter                           | 80EC00012   |
| 105 keys standard USB PC keyboard (Black)               | 89T110009   |
| LCD VESA mounting bracket                               | 80EC00028   |

**Warranty:** 1 year ex-factory. Free 2 year warranty extension when the product is registered on the Praim web site

All names and trademarks contained in this document, are property of their respective owners. The information in this document is property of Praim SRL.

Ver. 1.00

